

Please read the instruction manual carefully before mounting!

Product Type: VEGA SURFACE

Product No: PL7U SERIES

Lamp Type: LED

- 220V / 50 Hz
- Aluminum Body
- PS/PMMA Diffuser

Application Areas:

- Corridors
- Shopping Mall
- Offices
- Schools

Disposal – Enviromental Protection

Don't throw old electrical products into the household waste. Recycle where facilities exist. Contact your local authorities or dealer for advice.



Technical Data:

- PL7U Surface Mounted Series
 - LED
 - IP40
 - Lumileds LED
- Tridonic/Osram Driver

1. Lighting fixture should be installed by an expert technician.
2. Remove the packaging of the fixture.
3. Open the nylon package which contains the assembly components.
4. Be sure that electric current is off.
5. To make the ceiling connection, drill 2 holes to the ceiling with 35mm depth by 7mm drill and place anchors to these holes.
6. Fix the sheet metal hangers to the anchors by the screws inside the package.
7. Unfix the fixture side lid near to the cable gasket.
8. Take the cables to the inside of the fixture through cable gasket.
9. Connect the phase and neutral cables to the outer contacts and the ground cable to the middle contact of the connection terminal.
10. Push the body of the fixture towards the sheet metal hangers until you hear the click sound.
11. Fix back the fixture side lid by screws to its place.

